

Compatibility List of Pylontech Low Voltage ESS and Inverters Ver.2.46.xlsx

48V ESS

Last Update: 2026/7/7

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver
		US3000D/US5000/US5000B/ UP5000D/UF5000/Pelio-L/ FB-L-5.12/FB-L-16/FB-L-20			Activation	Force Charge	
Victron Energy	Multiplus 48V (via Venus OS)	✓	CAN	On/off-grid ^a	Yes	Yes	422/V2.15
Victron Energy	Quattro 48V (via Venus OS)	✓	CAN	On/off-grid ^a	Yes	Yes	422/V2.15
SMA Solar Technology AG	SI 4.4-M	✓	CAN	On/off-grid ^d	No	Yes	
SMA Solar Technology AG	SI 6.0-H	✓					
SMA Solar Technology AG	SI 8.0-H	✓					
SMA Solar Technology AG	SI 6048US	✓					
Schneider-Electric	Conext XW Pro series	✓	CAN	On/off-grid	Yes	Yes	Gateway: V1.06 XW+ Pro: V1.04 (UL) / V1.05 (IEC)
Goodwe	GW-BP/SBP	✓	CAN	On-grid	Yes	Yes	
Goodwe	GW-ES/ES-C10 ^h	✓	CAN	On-grid	Yes	Yes	
Goodwe	EM	✓	CAN	On-grid	Yes	Yes	
Imeon Energy	IMEON 3.6	✓	CAN	On/off-grid	Yes	Yes	V1.7.6.5
Imeon Energy	IMEON 9.12	✓	CAN	On/off-grid	Yes	Yes	V1.7.6.5
Studer Innotec	Xtender 48V serie	✓	CAN	On/off-grid	Yes	Yes	R652
Studer Innotec	VarioString serie	✓	CAN	On/off-grid	Yes	Yes	R652
Studer Innotec	VarioTrack 48V serie	✓	CAN	On/off-grid	Yes	Yes	R652
Studer Innotec	Next3 serie	✓	CAN	On/off-grid	Yes	Yes	
Selectronic	SPMC 480	✓	CAN	On/off-grid	No	Yes	
Selectronic	SPMC 481	✓	CAN	On/off-grid	No	Yes	
Selectronic	SPMC 482	✓	CAN	On/off-grid	No	Yes	
Voltronic	Infinisolar series 48V ^b	✓	RS485(9600)/CAN	On/off-grid	Yes	Yes	V1.00
Voltronic	Axpert series 48V ^b	✓	RS485(9600)/CAN	On/off-grid	Yes	Yes	V2.61
Sofar	ME3000SP	✓	RS485(115200)/CAN	On-grid	Yes	Yes	V1.2
Sofar	HYD series	✓	RS485(115200)/CAN	On-grid	Yes	Yes	V1.2
CHINT POWER	ECH3K ~ 6K-SML-EU	✓	CAN	On/off-grid	Yes	Yes	LCD: 29.08
CHINT POWER	ECA3K ~ 6K-SNL-EU	✓					DSP: 05.95
APsystems	EZHI series	✓	CAN	On/off-grid	Yes	Yes	1.0.4.0
APsystems	ELS-5	✓	CAN	On-grid	Yes	Yes	Hardware version Rev1.2.4 Software version Rev1.2.X
APsystems	ELT-12	✓	CAN	On/off-grid	Yes	Yes	1.1.5.10_1.1.3.12_1.0.11.0
APsystems	ELS-11.4	✓	CAN	On/off-grid	Yes	Yes	1.1.6.X
APsystems	AHS-6.3	✓	CAN	On/off-grid	Yes	Yes	1.1.6.X
Sermatec	SMT-5K-TL-LV	✓	RS485(9600)/CAN	On/off-grid	Yes	Yes	
Zucchetti Centro Sistemi	Azzurro 3000SP	✓	RS485(115200)/CAN	On-grid	Yes	Yes	V1.2
Zucchetti Centro Sistemi	Azzurro HYD3000/6000-ES	✓	RS485(115200)/CAN	On-grid	Yes	Yes	V1.2
Solis	RHI/RAI series	✓	CAN	On/off-grid	PV only	Yes	90009
Solis	S5-EA1P-L / S5-EH1P-L series	✓	CAN	On/off-grid	Yes	Yes	
Solis	S6-EA1P-L / S6-EO1P-48(-EU)	✓	CAN	On/off-grid	Yes	Yes	
Solis	S6-EH1P-L / S6-EH1P-L-PLUS / S6EH1P-NV-YD-L	✓	CAN	On/off-grid	Yes	Yes	
Solis	S6-EH2P-SV-YD-L(-US)	✓	CAN	On/off-grid	Yes	Yes	
Solis	S6-EH3P-NV-YD-L / S6-EH3P-LV-YD-L	✓	CAN	On/off-grid	Yes	Yes	
Deye (Sunsynk)	SUN-SG01LP1 series	✓	CAN	On/off-grid	Yes	Yes	V1586
Deye (Sunsynk)	SUN-SG03LP1 series	✓	CAN	On/off-grid	Yes	Yes	V1586
Deye (Sunsynk)	SUN-SG04LP1 series	✓	CAN	On/off-grid	Yes	Yes	
Deye (Sunsynk)	SUN-SG04LP3 series	✓	CAN	On/off-grid	Yes	Yes	
Deye (Sunsynk)	SUN-SG05LP3 series	✓	CAN	On/off-grid	Yes	Yes	
Deye (Sunsynk)	SUN-OG02LP1 series	✓	CAN	On/off-grid	Yes	Yes	

Please note that compatibility testing with various inverter brands is currently underway. The list will be updated regularly.
For any inquiries, please contact: service@pylontech.com.cn

Compatibility List of Pylontech Low Voltage ESS and Inverters Ver.2.46.xlsx

48V ESS

Last Update: 2026/7/7

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver
		US3000D/US5000/US5000B/ UP5000D/UF5000/Pelio-L/ FB-L-5.12/FB-L-16/FB-L-20			Activation	Force Charge	
Alpha & Outback Energy	SPCIII-5000-48	✓	RS485 (9600)	Off-grid	Yes	Yes	91.24
Alpha & Outback Energy	SPCIII-7200-48	✓					45.06
Alpha & Outback Energy	SPCIIIS-5000-48	✓					71.1
Lux Power	LXP 3-6K Hybrid	✓	CAN	On/off-grid	Yes	Yes	AA1.0
Lux Power	ACS series	✓					AA1.0
Lux Power	SNA series	✓					AA1.0
Lux Power	LXP-LB-EU Series	✓					EA1.0 (for 8K/10K model)
Lux Power	LXP-LB-US Series	✓					fA1.0 (for 12K model)
Sungrow	MG-5/6/8/10-RL Series	✓	CAN	On-grid	Yes	Yes	
Sinexcel-Isuna	Isuna 3000S-6000S/SO	✓	CAN	On-grid	Yes	Yes	ARM V127
Sinexcel-Isuna	Isuna D5-12K-SL/TL/SL-S/TL-S	✓	CAN	On-grid	Yes	Yes	ARM V8.0
Sinexcel-Isuna	Isuna 8000SO-12000SO	✓	CAN	On-grid	Yes	Yes	ARM V112
Sinexcel-Isuna	Isuna O1.5K-O6K-SOL-G2	✓	CAN	On-grid	Yes	Yes	ARM V5.0
Morningstar	TriStar MPPT in 48V	✓	N/A	On/off-grid	PV only	No	v32b
Morningstar	TriStar MPPT 600V in 48V	✓	N/A	On/off-grid	PV only	No	v32b
Morningstar	TriStar PWM TS-45 in 48V	✓	N/A	On/off-grid	PV only	No	v32b
Morningstar	GS-MPPT-60M/80M/100M-200V ^f	✓	CAN	On/off-grid	PV only	No	v2.0
Delios s.r.l.	DLS/C series	✓	CAN	On/off-grid	No	Yes	A 1.30; B 1.18; C1.27
Delios s.r.l.	DLS AC series	✓	CAN	On/off-grid	No	Yes	A 1.30; B 1.18; C1.27
Ingeteam Power Technology	ISS 1Play TL M series	✓	CAN	On/off-grid	Yes	Yes	ABH1007_D
MLT	Oasis 448	✓	N/A	Off-grid	No	Yes	V2.19
MLT	Oasis 648	✓	N/A	Off-grid	No	Yes	V2.19
Steca	Solarix PLI 5000-48	✓	N/A	Off-grid	Manual	No	
SAJ	Sunfree series	✓	RS485(9600)	On/off-grid	Yes	Yes	V2.031/V1.037
SAJ	H1 series	✓	CAN	On/off-grid	Yes	Yes	V2.094/V1.318
SolarMax	ES series	✓	CAN	On/off-grid	No	Yes	A 1.30; B 1.18; C1.27
SolarMax	AC series	✓	CAN	On/off-grid	No	Yes	A 1.30; B 1.18; C1.27
NEP	BDH-8K/10K/12KSP-LB	✓	CAN	On/off-grid	Yes	Yes	
SONNEX	STH3.6-6KSH-L	✓	CAN	On/off-grid	Yes	Yes	DSP:2033 ARM:8020
Growatt	SPH 3000 - 6000	✓	CAN	On/off-grid	No	Yes	RA1.0
Growatt	SPF 2000 - 5000 HVM-48/ LVM-48P ^c	✓	RS485(9600)	On/off-grid	No	Yes	GW500.08/502.05/503.03/507.03
Growatt	SPF 5000 ES / SPF 6000 ES PLUS	✓	CAN	On/off-grid	Yes	Yes	Main CPU 067.02 / Slave CPU 068.02
Growatt	SPF 12000T DVM-US	✓	CAN	On/off-grid	Yes	Yes	
Growatt	M2000H/3000H/5000H - 48 ^c	✓	RS485(9600)	On/off-grid	No	Yes	SK001.11/012.06/013.03/035.00

Compatibility List of Pylontech Low Voltage ESS and Inverters Ver.2.46.xlsx

48V ESS

Last Update: 2026/7/7

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver
		US3000D/US5000/US5000B/ UP5000D/UF5000/Pelio-L/ FB-L-5.12/FB-L-16/FB-L-20			Activation	Force Charge	
Sol-Ark	Sol-Ark-5K/8K-48-ST	✓	CAN	On/off-grid	Yes	Yes	V1430
Sol-Ark	Sol-Ark-5K-120V	✓	CAN	On/off-grid	Yes	Yes	V1430
Sol-Ark	Sol-Ark-8K-120/230V	✓	CAN	On/off-grid	Yes	Yes	V1430
Sol-Ark	Sol-Ark-8K-230-1P	✓	CAN	On/off-grid	Yes	Yes	V1430
Sol-Ark	Sol-Ark-12K-P,	✓	CAN	On/off-grid	Yes	Yes	V1430
Sol-Ark	Sol-Ark-12K-3P-380V	✓	CAN	On/off-grid	Yes	Yes	V1430
Sol-Ark	Limitless 15K-LV	✓	CAN	On/off-grid	Yes	Yes	V1430
AXIOMA energy	ISPWM 5000	✓	N/A	On/off-grid	No	No	
AXIOMA energy	ISMPPT BF 3000 - 5000	✓	N/A	On/off-grid	No	No	
AXIOMA energy	ISGRID (BF) 3000 - 5000	✓	N/A	On/off-grid	No	No	
Phocos	Any-grid PSW-H-5kW-230/48V	✓	RS485(9600)	On/off-grid	Yes	Yes	V1.00
Western CO.	LEONARDO PRO 3000/48 Li (via Western LK3)	✓	CAN	On/off-grid	Yes	Yes	V1.1
EFFEKTA	AX-M1 4000/5000-48 (via Com Box)	✓	RS485(9600)	On/off-grid	Yes	Yes	54.40/74.40
EFFEKTA	AX-K1 4000/5000-48 (via Com Box)	✓	RS485(9600)	On/off-grid	Yes	Yes	14.40/34.40
EFFEKTA	AX-M2 4000/5000-48	✓	RS485(9600)	On/off-grid	Yes	Yes	51.00/72.01
Kehua	SPH5000-BL	✓	CAN	On-grid	Yes	Yes	V1.00.013
Noark	Ex9N-DH-3~8KS-AU series	✓	CAN	On/off-grid	Yes	Yes	V1139
Noark	Ex9N-DH-5~12KT-AU series	✓	CAN	On/off-grid	Yes	Yes	V1139
HYPONTECH	HES 3000 - 6000	✓	CAN	On/off-grid	Yes	Yes	DSP: V1.0.0.21 ARM: V1.0.0.12
INVT	BD series(1) XD3~6KTL series(2)	✓	CAN	On/off-grid	Yes	Yes	V1.06(1) 417-412-207(2)
TBB	Kinergier Pro: CK-II 2.0S-3.0S (1)	✓	CAN	On/off-grid	No	Yes	LCD:V1.13 DSP:V1.24(1) LCD:V1.14 DSP:V1.11(2) LCD:V1.28 DSP:V1.30(3)
TBB	CK-II 2.0M-3.0M(2), CK4.0S-8.0S(3)	✓			No		LCD:V1.13 DSP:V1.24(1) LCD:V1.14 DSP:V1.11(2) LCD:V1.28 DSP:V1.30(3)
TBB	Kinergier Pro-II: CK-II 3.0M-8.0S	✓			Yes		LCD:V2.00 DSP:V2.00
TBB	RiiO: 2KVA - 6KVA(1)	✓			Yes		LCD:V1.11 DSP:V2.06 (1)
TBB	RiiO II: 3KVA - 8KVA(2)	✓			Yes		LCD:V1.04 DSP:V1.03(2)
TBB	RiiO Sun: 2KVA - 6KVA(3)	✓			Yes		LCD:V1.11 DSP:V2.06 MPPT:V1.10(3)
TBB	RiiO Sun II: 3KVA - 8KVA(4)	✓			Yes		LCD:V1.04 DSP:V1.03(4)
TBB	Apollo Matrix: 3.0M-5.0S	✓			Yes		LCD:V1.15 DSP:V1.24 MPPT:V1.10
TBB	Apollo Maxx: 2.0M-5.0S	✓			Yes		LCD:V1.11 DSP:V1.11 MPPT:V1.10
TBB	Tyrann Series: 10.0S-15.0S	✓			Yes		LCD:V1.0 DSP:V1.0
EPEVER	UP3000-HM5041(RTU)	✓	RS485(115200)		Yes	Yes	SV1.73
EPEVER	UP3000-HM8041(RTU)	✓					SV1.82
EPEVER	UP3000-HM5042(RTU)	✓					SV1.83
EPEVER	UP5000-HM8042(RTU)	✓					SV1.84
Afore	AF1~3.6K-SL-1 Series	✓	CAN	On/off-grid	Yes	Yes	1.01
Afore	AF3~6K-SL Series	✓	CAN	On/off-grid	Yes	Yes	1.01

Compatibility List of Pylontech Low Voltage ESS and Inverters Ver.2.46.xlsx

48V ESS

Last Update: 2026/7/7

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver
		US3000D/US5000/US5000B/ UP5000D/UF5000/Pelio-L/ FB-L-5.12/FB-L-16/FB-L-20			Activation	Force Charge	
Afore	AF4~6K-SLP Series	√	CAN	On/off-grid	Yes	Yes	1.01
Afore	AF1~3.6K-ASL-1 Series	√	CAN	On/off-grid	Yes	Yes	1.01
Afore	AF3~6K-ASL Series	√	CAN	On/off-grid	Yes	Yes	1.01
Afore	AF1~6K-SL-0 Series	√	CAN	On/off-grid	Yes	Yes	1.01
Afore	AF1~6K-ASL-0 Series	√	CAN	On/off-grid	Yes	Yes	1.01
MUST	PV1800 VHM 3KW - 5.5KW	√	CAN	On/off-grid	No	Yes	1.17.06
Moixa	Smart Battery V4 3000	√	CAN	On-grid	Yes	Yes	V2.2.1
Moixa	GridShare Hub	√	CAN	On-grid	Yes	Yes	V2.2.1
MEGAREVO	RKL1 Series	√	CAN	On/off-grid	Yes	Yes	ARM: 1.00.28 DSP: 1.01.23
MEGAREVO	R5K/6K/7K/8KLNA	√	CAN	On/off-grid	Yes	Yes	ARM:1.03.12 DSP:1.04.11
AISWEI	ASW3000/3680/4000/5000/6000H-S2	√	CAN	On/off-grid	Yes	Yes	
AISWEI	ASW003K/004K/005K/006K-BH-M2	√		On/off-grid	Yes	Yes	
AISWEI	ASW008K/010K-SH	√	CAN/485	On/off-grid	Yes	Yes	
SOROTEC	REVO II - 48V Series	√	CAN	On/off-grid	Yes	Yes	Inverter:1.5.4 Control board: 64
SOROTEC	REVO E PLUS - 48V Series	√		On/off-grid			
SOROTEC	REVO VM II - 48V Series	√		Off-grid			
SOROTEC	REVO VM PLUS - 48V Series	√		Off-grid			
FSP Power Solution GmbH	PowerManager series 4-15kW Offgrid PMI III / Zero	√	RS485(9600)	On/off-grid	Yes	Yes	V1.00 V2.61
Senergy	SE 4K6/5K/6KHB-60/120	√	RS485(9600) ^e	On/off-grid	PV only	Yes	0.6.0
Senergy	SE 4K6/5K/6KAC	√		On/off-grid	No	Yes	
Livoltek	Hyper series	√	CAN	On/off-grid	Yes	Yes	1.78
Livoltek	Retro series	√		Off-grid	Yes	Yes	ARM V0.59 DSP V0.13
Livoltek	GF1-3K/5K48S1	√					
Livoltek	BV1-3K/5K48S1	√					
Hoymiles	HYS-LV Series	√	CAN	On/off-grid	Yes	Yes	Power - V01.04.19 and above Safety - V01.02.13 and above System - V00.02.18 and above
Hoymiles	HAS-LV Series	√		On/off-grid	Yes	Yes	
Solavita	SWH3600 ~ 6000L-S1-SR	√	RS485	On/off-grid	Yes	Yes	V2.85.37
Solavita	SWH008 ~ 012KL-S1-SR	√	RS485	On/off-grid	Yes	Yes	V8.31.13
CE+T	Sierra 25 (48Vdc)	√	CAN	On/off-grid	Yes	No	V16.4.0
SRNE	HF/HFP/HESP/HYP Series	√	RS485	On/off-grid	Yes	Yes	
SRNE	ASF/ASP/ABP Series	√	RS485	On/off-grid	Yes	Yes	
EAST	EAHI-3000 ~ 6000-SL	√	RS485	On/off-grid	Yes	Yes	master V1001, dsp V1004
LEDIT	FVDi series	√	CAN	On/off-grid	No	Yes	A 1.30; B 1.18; C1.27
Growocol	MKS IV 5.6KW -B	√	RS485(9600)	On/off-grid	Yes	Yes	
Growocol	MKS IV 6KW TWIN	√	RS485(9600)	On/off-grid	Yes	Yes	
Growocol	MAX II-8000	√	RS485(9600)	On/off-grid	Yes	Yes	
OPTI-Solar	SP5000 Brilliant series	√	RS485(9600)	On/off-grid	Yes	Yes	V1.00/00.32
OPTI-Solar	SP5000 Regal/Handy Plus	√	RS485(9600)	On/off-grid	Yes	Yes	V1.00/00.32
OPTI-Solar	SP4000/10000 Premium	√	RS485(9600)	On/off-grid	Yes	Yes	V1.00/00.32

Compatibility List of Pylontech Low Voltage ESS and Inverters Ver.2.46.xlsx

48V ESS

Last Update: 2026/7/7

Inverter Brand	Inverter Type	Battery	COMM.	Application	Key Features		Firmware Ver
		US3000D/US5000/US5000B/ UP5000D/UF5000/Pelio-L/ FB-L-5.12/FB-L-16/FB-L-20			Activation	Force Charge	
^a When compatible with Victron Multi/Quattro in off-grid application via Venus-device, it is required to have a Victron MPPT or other compatible PV inverter with Victron to avoid the system getting shut down. ^b When compatible with Voltronic Axpert series, only VM III and King two types are available for RS485 communication, for the rest types of Axpert only available for manual settings. When using VM III and King, only launch firmware 02.61 or higher can work with Force L1/L2. When using Fidus Plus/Max combine with Voltronic inverter, please use CANBUS communication and the inverter may need firmware upgrade, for the corresponding supported inverter firmware please consult with Voltronic. ^c When compatible with Growatt SPF/M series corresponding type, according to inverter logic, the depth of discharge(DoD) of battery shall be set to 80% or lower. Otherwise may lead to system shut down and need of manually recharge battery. ^d When compatible with SMA SI4.4-M / SI6.0-H / SI8.0-H, it's required to follow the min. configuration table from SMA for a guaranteed configuration. The Force L1/L2 is not compatible with SMA SI series. ^e When compatible with Senergy inverter, max. configure 1 string of battery system, donot support multiple strings' connection. ^f When compatible with GS-MPPT-60M/80M/100M-200V, it requires optional ReadyBMS accessory. ^g When compatible withP721730001, please make sure the discharge cut off voltage is higher than 47V. ^h Not Compatible with Pelio-L and UF5000.							